

# BOOSTER 2G

## LONG RANGE VEHICLE AND DRIVER IDENTIFICATION



### KEY FEATURES:

- Long range driver ID up to 10 m (33 ft)
- Supported credentials
  - HID prox, EM, Nedap
  - MIFARE, HID iClass, LEGIC, Calypso
- One card solution
- Simultaneous driver & vehicle ID
- Maximizes perimeter security

The Boosters enables long range driver identification. Driver based ID systems ensure that a vehicle can never get access to a secured area unless occupied by an authorized driver. The Booster is used in combination with a personal access credential. It is an easy to integrate solution for vehicle access, which eliminates the need to issue new cards.

### Driver based identification, how does it work?

The driver based tag is made up of two elements.

- 1) Building access card
- 2) In-vehicle Booster

The Booster is placed on the windshield on the inside of a vehicle. When an authorized building access card is inserted into the Booster it will be read and then boosted to the external Nedap TRANSIT reader. The TRANSIT reader transmits the credential ID to any standard back end security panel. If the credential is authorized and access is granted the gate will open automatically. Removal of the Driver ID is ensured by designing the system to require that the access card is also used for building access.

### Matching vehicle and driver

Optionally a separate ID (vehicle ID) can be programmed in the Booster hardware on certain models, this allows you to match the right driver with the right vehicle.

Boosters are available for almost all card technologies:

**Prox-Booster 2G;** supporting proximity access control badges operating on 120-125 kHz such as HID prox, EM and Nedap.

**Smartcard-Booster 2G;** supports ISO 14443 or 15693 compliant smartcards (eg. MIFARE, MIFARE DESFIRE, LEGIC, Calypso and HID iClass) operating on 13.56 MHz. Depending on applied card technology either CSN or sector information can be read, see [Booster\\_Installguide](#) for more information.

**Transition-Booster 2G;** supports proximity (120-125 kHz) as well as smartcard (13.56 MHz) technology. The Transition-Booster is specifically designed to be used in applications where multiple card technologies are applied simultaneously. It allows for seamless migration from existing Prox to versatile smartcard applications.

### Booster applications

Typical applications for the Booster are high secured areas like airports, seaports, military bases, utility companies, corporate and educational campuses, police, fire and other installations where vehicles must be assigned to a specific driver.

# SPECIFICATIONS

TECHNICAL INFORMATION	PROX-BOOSTER 2G	SMARTCARD-BOOSTER 2G	TRANSITION-BOOSTER 2G
Part no.	9948538 Prox-Booster 2G 9948546 Prox-Booster 2G Single	9895337 Smartcard-Booster 2G	9948562 Transition-Booster 2G
Operating frequency	120 kHz / 2.45 GHz	13.56 MHz / 2.45 GHz	120 kHz / 13.56 MHz / 2.45
Dimensions	116 x 72 x 27 mm [4.6 x 2.8 x 1.1 in] according to Ertico OBU standard		
Weight	95 gram [3.4 oz]	120 gram [4.2 oz]	120 gram [4.2 oz]
Protection	IP32 [approx. NEMA 2]		
Color	Grey, according to RAL 7016		
Operating	-40 ... +85°C [-40 ... +185°F]		
Storage temperature	-40 ... +85°C [-40 ... +185°F]		
Detection range	Up to 10 meters [33 feet] with TRANSIT Standard, up to 4 meter [12 ft] with TRANSIT Entry		
Humidity	10% ... 93% relative humidity, non condensing		
Mounting	Attaches with suction pads to the windscreen on the inside of a vehicle. In case of a metallised windscreen a metal free communication window is required.		
Certification	EN60950, EMC 89/336/EEC, EN50081-1, EN 50082-1, ETS 0908 and FCC		
Battery life	User replaceable AAA lithium batteries with expected lifetime of 5 years*.	User replaceable AAA lithium batteries with expected lifetime of 5 years*.	User replaceable AAA lithium batteries with expected lifetime of 5 years*.
Note	*Life time expectation is based on: <ul style="list-style-type: none"> <li>▪ Average warm climate conditions. Exposure to extreme hot conditions might reduce battery life.</li> <li>▪ Default operating mode C</li> </ul>		
Operating mode	C: After user activation vehicle and driver ID is transmitted (default)  A: Continuous transmission of vehicle ID and driver ID *  E: Continuous transmission of vehicle ID and driver ID without need to activate the switch, not even initially when card is inserted.  * This option is not available for the Prox-Booster 2G single ID !	C: After user activation vehicle and driver ID is transmitted (default)  A: Continuous transmission of vehicle ID and driver ID  E: Continuous transmission of vehicle ID and driver ID without need to activate the switch, not even initially when card is inserted.	C: After user activation vehicle and driver ID is transmitted (default)  A: Continuous transmission of vehicle ID and driver ID  E: Continuous transmission of vehicle ID and driver ID without need to activate the switch, not even initially when card is inserted.
Inductive readable	Only the Prox-Booster's embedded Booster ID.	Embedded Booster ID (vehicle ID)	Embedded Booster ID (vehicle ID)
Identification Driver	Prox-Booster: Driver ID & vehicle ID Prox-Booster single id: Driver ID	Driver ID & vehicle ID	Driver ID & vehicle ID
Supported prox cards (120-125 kHz cards)	EM/ Nedap / HID PROX up to 40 bits (HIB required on reader level 7819102)		EM/ Nedap/ HID PROX up to 40 bits (HIB required on reader level 7819102)
Supported smartcards (13.56 MHz)*		ISO 14443 1/2A/3A ISO 15693 1/2/3 - MIFARE CSN and optional sector information - MIFARE DESFire CSN and file data - LEGIC Advant UID - HID iCLASS CSN - Calypso PUPI and public files See for more information Smartcard Config Program	ISO 14443 1/2A/3A ISO 15693 1/2/3 - MIFARE CSN and optional sector information - MIFARE DESFire CSN and file data - LEGIC Advant UID - HID iCLASS CSN - Calypso PUPI and public files See for more information Smartcard Config Program
Readers	9990410 TRANSIT PS270 Standard reader 9875220 TRANSIT PS270 Standard reader USA 9876200 TRANSIT Entry		